

# ADVANTECH



## Customer Logo



© 2023 Advantech Czech s.r.o. No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photography, recording, or any information storage and retrieval system without written consent. Information in this manual is subject to change without notice, and it does not represent a commitment on the part of Advantech.

Advantech Czech s.r.o. shall not be liable for incidental or consequential damages resulting from the furnishing, performance, or use of this manual.

All brand names used in this manual are the registered trademarks of their respective owners. The use of trademarks or other designations in this publication is for reference purposes only and does not constitute an endorsement by the trademark holder.

# Used symbols



*Danger* – Information regarding user safety or potential damage to the router.



*Attention* – Problems that can arise in specific situations.



*Information* – Useful tips or information of special interest.



*Example* – Example of function, command or script.

# Contents

<b>1. Changelog</b>	<b>1</b>
1.1 Customer Logo Changelog . . . . .	1
<b>2. Customer Logo Router App</b>	<b>2</b>
<b>3. Web Interace</b>	<b>2</b>
3.1 Configuration . . . . .	2
3.2 Insert your own logo into the installation file . . . . .	2
3.2.1 How to generate your own UM Customer Logo . . . . .	3
<b>4. Related Documents</b>	<b>4</b>

## List of Figures

1 Router app menu . . . . .	2
-----------------------------	---

## List of Tables

# 1. Changelog

## 1.1 Customer Logo Changelog

### v1.0.0 (2020-01-31)

- First release.

### v1.1.0 (2020-10-01)

- Updated CSS and HTML code to match firmware 6.2.0+.

## 2. Customer Logo Router App

*Customer Logo* router app allows to change the router's logo in web interface.



Router app *Customer Logo* is not contained in the standard router firmware. Uploading of this router app is described in the Configuration manual (see Chapter [Related Documents](#)).



This router app is intended only for Advantech industrial routers manufactured with **FW 6.2.0 or later** and is **not supported** by routers of **v2 platform**.

## 3. Web Interface

For configuration of the *Customer Logo* router app a web interface is available. It can be invoked by pressing the module name on the *Router apps* page of the router's web interface.

Left part of the *Customer Logo* module web interface contains menu with section *Configuration* and section *Customization*, see the figure 1. *Configuration* section contains only the *Logo* item and *Customization* section contains only the *Return* item that switches the module's web interface back to the main interface of the router.

### Customer Logo

Configuration	Update logo
Logo	New logo (PNG File, max. 10 kB) <input type="button" value="Choose File"/> No file chosen
Customization	<input type="button" value="Update"/>
Return	

Figure 1: Router app menu

### 3.1 Configuration

To set your own logo into the web interface, use the *Choose File* button, select the logo file (maximum size of 10 kB) and click on the *Update* button. Use the *Return* button to return to the router's web interface.



Use *Shift + F5* to reload your current page (this will update your browser's cache).

### 3.2 Insert your own logo into the installation file

This modification of the installation file allows you to install the UM *Customer Logo* with your logo in the future.

### 3.2.1 How to generate your own UM Customer Logo

- Insert your logo into the web interface as described above.
- Open a command line or other terminal application on your computer, enter the following command  
`ssh root@192.168.1.1`  
(if you have changed the local IP address of your router please update the command accordingly) and press Enter.
- The program will ask you for the root password. Type it and press Enter.
- Paste the script according to the version of your router (described below).
- Download the updated version of the UM Customer Logo installation file. Links for modified module are described below.

#### Script for v2i routers:

```
cp -r /opt/customerlogo /tmp/customerlogo
rm -f /tmp/customerlogo/etc/logo.png
mv /tmp/customerlogo/etc/settings /tmp/customerlogo/etc/defaults
cd /tmp
tar -czvf customerlogo.v2.tgz customerlogo/
ln -s /tmp/customerlogo.v2.tgz /opt/customerlogo/www/customerlogo.v2.tgz
```

#### Script for v3 routers:

```
cp -r /opt/customerlogo /tmp/customerlogo
rm -f /tmp/customerlogo/etc/logo.png
mv /tmp/customerlogo/etc/settings /tmp/customerlogo/etc/defaults
cd /tmp
tar -czvf customerlogo.v3.tgz customerlogo/
ln -s /tmp/customerlogo.v3.tgz /opt/customerlogo/www/customerlogo.v3.tgz
```

#### Link for download UM Customer Logo with your logo

For v2i routers:

<https://192.168.1.1/module/customerlogo/customerlogo.v2.tgz>

For v3 routers:

<https://192.168.1.1/module/customerlogo/customerlogo.v3.tgz>

For v4 routers:

<https://192.168.1.1/module/customerlogo/customerlogo.v4.tgz>



If you have changed the local IP address of your router please update the command accordingly.

## 4. Related Documents

You can obtain product-related documents on *Engineering Portal* at [icr.advantech.cz](http://icr.advantech.cz) address.

To get your router's *Quick Start Guide*, *User Manual*, *Configuration Manual*, or *Firmware* go to the [Router Models](#) page, find the required model, and switch to the *Manuals* or *Firmware* tab, respectively.

The *Router Apps* installation packages and manuals are available on the [Router Apps](#) page.

For the *Development Documents*, go to the [DevZone](#) page.