



- + Powerful CPU and enhanced memory
- + LTE 450 MHz bands
- + Extended operational temperature range from -40 °C to +70 °C
- + 10-60 VDC operation with transient and reverse polarity voltage protection
- + Flexible port options 3-port Switch, Ethernet and RS-232/422/485 serial ports with isolation
- + MicroSD card holder, In/Out, USB Host
- + Low power consumption mode for solar and battery power applications
- + Optional industrial grade Wi-Fi
- + Optional PoE PSE or PoE PD on ETH0 and ETH1
- + Advanced security features

SmartFlex<sup>TM</sup> cellular router provides secure Internet connectivity for devices and LANs via the cellular networks using 450MHz frequency band. It canprovide automatic wireless failover for wired networks, wireless connectivity for devices in remote locations where cable connections are impractical and wireless connectivity for mobile assets. With upload speeds of up to 50 Mbps and download speeds of up to 100 Mbps, SmartFlex provides ample bandwidth, even for applications that require video.

SmartFlex SR307 places intelligence at the network edge with an extremely powerful Cortex A8 CPU at 1GHz, 256 MB flash memory, 512 MB RAM and 128kB M-RAM, providing full support for LTE (Long Term Evolution) speeds and applications. A secure Web interface allows users to configure and manage SmartFlex from remote locations. The router can also upgrade its configuration and firmware from the operator's central server, allowing for simultaneous mass reconfiguration of every router on the network. Users may insert Linux scripts and can create multiple configurations for the same router and switch from one configuration to another at any time. Modular SmartFlex can be configured for any application. Standard configuration includes 2 Ethernet ports with 2 independent LANs/IP addresses and also includes 1 USB host port, 1 microSD card holder, 2 SIM card holders for automatic failover to an alternate service provider, 2 binary inputs(I/O), 1 binary output (I/O).

An optional built-in Wi-Fi module is also available, with industrial grade operating temperature ranges from -40 to +70 °C. Further optional boards include: 3x ETH (the router can be configured with up to 5 total Ethernet ports and 3 independent LANs/IP addresses) or ETH/RS-232/485 or RS-232/485 (isolation strength up to 2.5kV) or RS-232. The SmartFlex supports real time data encryption and the creation of VPN tunnels using IPsec, OpenVPN and L2TP. It supports DHCP, NAT, NAT-T, DynDNS, NTP, VRRP, control by SMS, and numerous other functions, as well as additional software like SmartCluster VPN Server and R-SeeNet.



SmartFlex Family

2x ETH, 1x USB, 2x BI, 1x BO, MicroSD reader, 2x SIM reader

### BB - SR307 XXXXX - YYYY

	SWH	No SmartWorx HUB SmartWorx HUB
	Accessories 0 1	No Accessories (DIN holder included) Accessories with EU power supply
	5	International Power Supply (EU, US, UK, AUS)
	Enclosure 1 2	Plastic enclosure Metal enclosure
	Interfaces 0 1 3 4	No optional port 3x ETH Switch RS232 (5-pin TB), RS485/422 (4-pin TB) RS232 (4-pin TB), RS485 (3-pin TB), ETH
	D. 5	
	PoE 0 8 9	No PoE PoE PSE PoE PD
	WiFi 0 1	No Wi WiFi (TI 2.4 & 5 GHz)
	Router version 07	LTE 450MHz

### **ORDERING INFORMATION**

Note: Check with your local distributor for availability, options, and HW configuration. Contact Advantech B+B SmartWorx distributors.

Note: Antennas & Power Supply Sold Separately.



#### **HW SPECIFICATIONS**

PORTS, LED, ANTENNAS		
Up to 5x ETH ports	RJ45, 10/100 Mbps	
2× SIM	2 Mini SIMs (2FF) (rear panel)	
LED Indicators	PWR, DAT, WAN, ETH, SIM, USR, POE, INO, IN1, OUT	
2× ANT - ANT, DIV	SMA connectors	
1× Wi-Fi Antenna *Optional	R-SMA connector	
1× USB	USB Host connector 2.0	
1× SD Card	1x Micro SD Card slot (rear panel)	
RST	RESET button (rear panel)	
*Optional 3-port SWITCH	3x RJ45, 10/100 Mbps	
*Optional ETH - R232 - RS485	RJ45, 4-pin terminal block, 3-pin terminal block connectors – Isolation up to 2.5 kV	
*Optional RS232 - RS485	5-pin terminal block, 4-pin terminal block connectors – Isolation up to 2.5 kV	

POWER		
Power Supply	10 – 60 VDC (2–Way Molex connector)	
Power Consumption	Idle: 2.5 W Average: 4 W Peak: 11 W Sleep Mode: 10mW	
ENVIRONMENTAL		
Temperature Range	Operating: -40 to +70 °C Storage: -40 to +85 °C	
Humidity	Operating: 0 to 95 % Storage (Non-condensing): 0 to 95 %	
Cold Start	-35 °C	
Operating Altitude	2000 m / 70 kPa	
Ingress Protection Rating	IP30	

MECHANICAL		
Plastic or metal case with plastic or metal DIN rail		
Enclosure Dimensions	55x97x125 mm	
Weight Plastic	170 g	
Weight Metal	375 g	







WI-FI - 802.11 A/B/G/N, AP OR CLIENT MODES		
Supported Wi-Fi band	2.4 GHz, 5.4 GHz	
Encryption	None, WEP, TKIP, AES	
5 GHz supported channels	36, 40, 44, 48, 52, 56, 60, 64, 149, 153, 157, 161, 165	
2.4 GHz supported channels	1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 13, 14	
Number of clients	10	
Authentication	Open, Shared, WPA-PSK, WPA2-PSK	

POE PARAMETERS	POE PD parameters for opposite PSE	POE PSE
Input voltage range	42.5 – 57 V	44 – 57 V, 65 W
Power available	25.50 W	2x 25.50 W (ETH0, ETH1)
Maximum current	600 mA	
Insul. Strength	1.5 kV from the router	none
Standards IEEE 802.3at-2009 (PoE+) and IEEE 802.3af-2003 (PoE) supported. Cabling needed is Category 5, up to 12.5 $\Omega$ . It is possible to use a passive PoE injector		

### CELLULAR MODULE PARAMETERS

LTE features Bit rate 100 Mbps (DL) / 50 Mbps (UL), UE CAT. 3

3GPP rel. 9 standard

Supported bandwidths: 5 Mhz, 10 Mhz, 20 Mhz Supported frequencies: B31 (450 MHz) Rated Output Power: B31: CLASS 3


MIMO (Multi-Input Multi-Output) antenna support


Max power - typical 23 dBm



### STANDARDS AND REGULATIONS

INDUSTRY CERTIFICATIONS & APPROVALS		
	SR307 - LTE 450	
Radio	ETSI EN 301 908-1 V11.1.1, ETSI EN 301 908-13 V11.1.1, ETSI EN 300 328 V2.1.1, ETSI EN 301 893 V2.1.1	
EMC	ETSI EN 301 489-1 v1.9.2, ETSI EN 301 489-1 V2.1.1, Draft ETSI EN 301 489-52 V1.1.0, ETSI EN 301 489-17 V3.1.1	
Safety	EN 60950-1:2006 + A11:2009 + A1:2010 + A12:2011 + A2:2013 + AC:2011, EN 62311:2008	
Mark – EMC for devices in transportation	E-Mark homologation number: 10R – 04 7737	









ACCESSORIES		Variant of router without accessories	Accessories included in set	Accessories sold separately
ORDER CODE	DESCRIPTION			
BB-WR-600N	Antenna LTE 450 MHz		~	<b>~</b>
BB-AW-A2458G-FSRPK	Antenna Wi-Fi, 2.4 & 5.8 GHz		<b>~</b>	<b>✓</b>
BB-RPS-v3-M02-M	SmartFlex Power Supply, 12V/1A		<b>~</b>	<b>v</b>
BB-RPS-v3-PSE	SmartFlex Power Supply, 48V/1.35A (power cord required)			<b>✓</b>
BB-PWRCORD-US	USA - Power Supply Power Cord			<b>~</b>
BB-PWRCORD-EU	EU - Power Supply Power Cord			<b>✓</b>
BB-PWRCORD-UK	UK - Power Supply Power Cord			<b>~</b>
BB-PWRCORD-AUS	AU - Power Supply Power Cord			<b>~</b>
BB-SBD40	DIN Rail Clip - metal	<b>✓</b>	<b>~</b>	
BB-CPD3	DIN Rail Clip - plastic	•	<b>~</b>	
BB-KN-v3-M02-3	PS Cable 2-wire, MO 2 pins, 3m, v3 routers	<b>~</b>		<b>~</b>
BB-KIO-v3-M06-3	IO Cable 6-wire, 3m, v3 routers			<b>✓</b>
BB-CON-SFLEXSET	PWR connector, I/O connector + 8 pins	•	<b>✓</b>	<b>~</b>
Quick Start Guide		•	<b>~</b>	<b>✓</b>

#### **SW FEATURES**

SOFTWARE		
Network and Routing	DHCP Server, , DHCP Client, NAT/PAT, VRRP, Dynamic DNS client, DNS proxy, VLAN, QoS, NTP Client/ Server, IGMP, BGP, OSPF, RIP, SMTPS, SNMP v1/ v2c/ v3, Backup routes, PPP, PPPoE, SSL, Port Forwarding, Host Port Routing, Ethernet Bridging	
Security	HTTPS, SSH, VPN tunnels, SFTP, Firewall (IP Filtering, MAC address filtering, Inbound and outbound Port filtering), DMZ (via iptables)	
VPN Tunnelling	Open VPN client and server and P2P, L2TP, PPTP, GRE, EasyVPN, DMVPN, IPSec with IKEv1 and IKEv2	
Configuration	Web server, SSH, Four configuration switchable profiles, Automatic configuration update from server Backup configuration, Restore configuration	
Firmware Management	Automatic firmware update from server, Locally via LAN and USB or remotely OTA (HTTP, HTTPS), Over-the-Air software updates, Over-the-Air cellular module update from FW	
Diagnostic  One CLICK report – current configuration / factory identification / system log / kernel log / reboot log / routing table, Remote di SSH		
Status Network Status, DHCP Status, IPSec Status, Statistics history for last 60 days		
Log	System Log, Reboot Log, Kernel Log	
Controlling and Diagnostic	SMS, SNMP v1/v2c/v3, Statuses, Log	
Event Engine	StartUp script & Up/Down script (Bash), Digital Input, Network Parameters, Data Usage, Timer, Power, Device Temperature Report Types: RAP, SMS, email, SNMP Trap	
Other	IPv6 support	

### WebAccess/VPN

WebAccess/VPN is an advanced VPN management solution for safe interconnection of Advantech routers and LAN networks in public Internet. Connection among devices and networks can be regional or global and can combine different technology platforms and various wireless, LTE, fixed and satellite connectivities.

**WebAccess/VPN** provides an easy and secure connectivity platform for applications such as branch connection, remote access, machine monitoring in industry sectors like Utilities & Energy, Automation, Predictive maintenance, Industrial IoT for any end device types such as Computers, PLCs, RTUs, Cameras, Terminals...

# WebAccess/DMP<sub>2</sub>

WebAccess/DMP Generation 2 is an advanced Enterprise-Grade platform solution for provisioning, monitoring, managing and configuring Advantech's routers and IoT gateways. It provides a zero-touch enablement platform for each remote device.

With WebAccess/DMP, secure zero-touch pre-provisioning and pre-configuration is simple, regardless of how large your deployment is: from one device to thousands. The platform supports full multi-tenancy, with the possibility of permissions-enabled power-user oversight across tenancies.

## R-SEENET™

Router Management Software consisting of two parts:

- R-SeeNet Server application can be programmed to automatically send SNMP queries (Simple Network Management Protocol) to each router defined in the network. The application retrieves status information from the routers and records it in the SQL database.
- R-SeeNet PHP is a web-based application that accesses the SQL database and provides the network administrator detailed information on individual routers and network health.

